



ML4030-ACO

MSA Compliant 100G

CFP2-ACO Electrical Passive Loopback Modules

Rev B



Revision 1.0

➤ ML4030-ACO 4x32G Passive Loopback Module - Key Features

- ✓ Passive CFP2 loopback module, 4 TX & 4 RX Lanes operating at 32Gb/s per lane
- ✓ Programmable Power Dissipation up to 12 W covering all CFP2 power classes
- ✓ Custom Memory Maps
- ✓ RX_LOS-Alarm driven by TX_DIS control
- ✓ High performance Signal Integrity traces
- ✓ MSA compliant Digital Diagnostic and Monitoring Interface (DDMI)
- ✓ 3 Status LED indicator
- ✓ Built with advanced PCB material
- ✓ Temperature sensing
- ✓ Cut-Off Temperature preventing module overheating
- ✓ Hot Pluggable module

➤ LED Indicator

- ✓ **Green** (Solid): Signifies that the module is operating in high power mode.
- ✓ **Red** (Solid): Signifies the module is operating in low power mode.
- ✓ **Green/Red** (Blinking): Signifies that the module is overheated and the temperature high alarm is asserted.

➤ Operating Conditions

Recommended Operation Conditions						
Parameter	Symbol	Notes/Conditions	Min	Typ	Max	Units
Operating Temperature	TA		0		85	°C
Supply Voltage	VCC	Main Supply Voltage	3.00	3.3	3.60	V
Data Rate	Rb	Guaranteed to work up to 32 Gbps per lane	0		100	Gbps
Input/Output Load Resistance	RL	AC-Coupled, Differential	90	100	110	Ω
Power Class		Programmable to Emulate all power classes	0		12	W

Table of Contents

1.	General Description	4
2.	Functional Description	4
2.1	Management Data Interface – MDIO.....	4
2.2	Initialization Sequence	6
2.3	GLB_ALRM	7
2.4	CFP Register Set	8
2.5	User NVR Restore and Save Function (0xB004)	9
2.6	PRG_ALRMs	10
2.7	RX_LOS	10
2.8	Temperature Monitor	11
2.9	Insertion Counter.....	12
2.10	Programmable Power Dissipation & Thermal Emulation.....	12
2.11	Cut-Off Temperature.....	12
2.12	Module Control and Status Registers.....	13
3.	CFP2-ACO Pin Allocation	15
3.1	High Speed Signals	16
4.	NVR Register preloaded values	16

1. General Description

The ML4030-ACO is a CFP2 passive electrical loopback module with a hot pluggable form factor designed for high speed testing applications for CFP2 host ports. The ML4030-ACO is designed for 100 Gigabit Ethernet applications and provides 4x32G RX and TX lanes, a MDIO module management interface and all the CFP2 MSA hardware signals.

The ML4030-ACO loops 4-lane of 32 Gb/s transmit data from the Host back to 4-lane of 32 GB/s receive data to the Host.

The ML4030-ACO provides programmable power dissipation up to 12W allowing the module to emulate all the CFP2 power classes.

2. Functional Description

2.1 Management Data Interface – MDIO

The ML4030-ACO supports the MDIO interface specified in IEEE802.3 Clause 45.

The ML4030-ACO implements a dedicated MDIO logic block in the to handle the high rate MDIO data and a CFP register space that is divided into two register groups, the Non-Volatile Registers (NVR) and the Volatile Registers (VR). The NVRs are connected to a Non-Volatile Memory device (NVM) for ID/Configuration data storage. Over the internal bus system, the VRs are connected to a device that executes the Host control commands and reports various Digital Diagnostic Monitoring (DDM) data. Please Note that in the rest of this document, independently of implementation, CFP registers are also referred as NVRs or VRs.

The ML4030-ACO specifications are the following:

- ✓ Supports MDC rates up to 4MHz.
- ✓ CFP Registers at MDIO Device Address1 as specified by CFP MSA.
- ✓ Supports various Physical Addresses thus allowing communication with many modules plugged to the same Host with different Port Addresses (PRT_ADDR0-2) assigned.

CFP registers use fast memory to shadow the NVM data and the DDM data. The shadow registers decouple the Host-side timing requirements from the module's internal processing, timing, and hardware control circuit introduced latency.

CFP shadow register set meets the following requirements:


- ✓ It supports dual access from the Host and from module internal operations such as NVM and

DDM data transfers.

- ✓ It supports continuous Host access (read and write) with fast access memory at maximum MDC rates of 4 MHz.
- ✓ It allows the uploading of NVM content into the CFP shadow register during module initialization. Data saving from CFP shadow register to NVM is supported.
- ✓ It supports the DDM data update periodically during the whole operation of the module. The maximum data refresh period is 1ms (real time temperature monitoring).
- ✓ It supports the whole CFP register set including all NVRs and VRs.
- ✓ Incomplete or otherwise corrupted MDIO bus transactions are purged from memory and disregarded.
- ✓ The port address is allowed to change on the fly without a module reset.

2.2 Initialization Sequence

The Startup sequence for the ML4030-ACO is defined below:



MOD_RSTs assertion drives the CFP2 module to a reset state, at this stage the MDIO interface will be held in a high impedance state, the Host will read 'FFFF'h from any address, while host write operations will have no effect.

Upon the de-assertion of MOD_RSTs, the CFP2 module exists to an initialize state which is a transient state.

The Initialization time required is less than one second. When Initialization state is completed, the CFP2 module will enter a Low-Power state; at this point MDIO becomes available for R/W operations.

2.3 GLB_ALRM

Below is the flowchart for GLB_ALRM signal during CFP states transitions:



GLB_ALRM is de-asserted during Reset and Initialize state, it is asserted in Low-Power, High-Power-up, TX-Off and TX-Turn-on states, then de-asserted again when Ready state is reached.
 GLB_ALRMn is the hardware pin, and is the inverse of GLB_ALRM.

The below example can be run in order to check for correct module initialization and GLB_ALRM signal:

- Assert MOD_LOPWR and TX_DIS, Deassert MOD_RSTn : GLB_ALRMn should be HIGH (module in Reset state)
- Assert MOD_RSTn (module exits Reset state into Low Power state) : GLB_ALRMn should be LOW
- Deassert MOD_LOPWR (module exits Low Power into TX-Off state) : GLB_ALRMn should stay LOW
- Deassert TX_DIS (module enters Ready state): GLB_ALRMn should go HIGH MDIO Signals, Addressing and Frame Structure.

Port Address (PRTADR)

As per the port address used, the module will work on any MDIO Physical port address which can be set by the HW input signals PRTADR [2:0]. So when using 2 or more CFP2 slots, each of them can be configured to a different Port Address.


PRTADR0	MDIO Physical Port address bit 0	I	1.2V LVCMOS
PRTADR1	MDIO Physical Port address bit 1	I	1.2V LVCMOS
PRTADR2	MDIO Physical Port address bit 2	I	1.2V LVCMOS

Device Address (DEVADD)

MDIO Device Address consists of 5 bits that are sent in MDIO frames, CFP MSA specifies that CFP register Set should be addressed using Device Address = 1, Thus CFP register space is available in the ML4030-ACO on D.A=1.

MDIO Frame

The Below Frame shows all segments of an MDIO Packet, PHYADR are the 5 bits Physical Address and DEVADD are the 5 bits Device Address.



ST = start bits (2 bits),

OP = operation code (2 bits),

PHYADR = physical port address (5 bits),

DEVADD = MDIO device address (or called device type, 5 bits),

TA = turn around bits (2 bits),

16-bit ADDRESS/DATA is the payload.

2.4 CFP Register Set

All registers are supported in memory map (Refer to table below), the set of registers starting from 0x8000 to 0x9F00 are implemented as NVR registers and all these registers are always read from NVM during initialization and mapped to corresponding addresses.

All VR (Volatile Registers) are set to zero or to MSA defaults value upon module initialization.

The NVR values are saved to NVM by calling the SAVE NVR function. The base ID registers are initially set, but the user can change them if required.

Hex Addr Start	Hex Addr End	Access Type	Allocated Size	Data Bit Width	Description
0000	7FFF	N/A	32768	N/A	Reserved for IEEE 802.3 use.
8000	807F	RO	128	8	CFP NVR 1. Basic ID Registers
8080	80C6	RO	128	8	CFP NVR 2. Extended ID Registers
80C8	80FF				CFP NVR 2. MSA-100GLH Module Alarm/Warning Threshold Registers
8100	817F	RO	128	8	CFP NVR 3. Network Lane BOL Measurement Registers
8180	81FF	RO	128	8	CFP NVR 4. MSA-100GLH Extended ID Registers
8200	83FF	RO	4x128	N/A	MSA Reserved
8400	847F	RO	128	8	Vendor NVR 1. Vendor Data Registers
8480	84FF	RO	128	8	Vendor NVR 2. Vendor Data Registers
8500	87FF	RO	6x128	N/A	MSA Reserved
8800	887F	RW	128	8	User NVR 1. User Data Registers
8880	88FF	RW	128	8	User NVR 2. User Data Registers
8900	8EFF	RO	12x128	N/A	MSA Reserved
8F00	8FFF	N/A	2x128	N/A	Reserved for User private use
9000	9FFF	N/A	4096	N/A	Reserved for Vendor private use
B000	B07F	RW	128	16	MSA-100GLH Module VR1: Command/Setup/Control/FAWS Registers
B080	B17F	RO	2x128	N/A	MSA Reserved
B180	B2FF	RW	3x128	16	MSA-100GLH Module VR1: Network Lane FAWS/Status Registers
B300	B57F	RW	5x128	16	MSA-100GLH Module VR2: Network Lane Control/Data Registers
B580	B5FF	RW	128	16	MSA-100GLH Module VR2: Network Lane OTN/FEC-related Registers (Optional)
B600	B6FF	RW	2x128	16	MSA-100GLH Module VR1: Host Lane FAWS/Control/Status Registers
B700	B77F	RW	2x128	16	MSA-100GLH Module VR1: Host Lane OTN/FEC-related Registers (Optional)
B780	B7FF	RO	128	N/A	MSA Reserved
B800	BAFF	RW	6x128	16	MSA-100GLH Module VR2: Network Lane Modulation Format Dependent Registers (Optional-informative)
BB00	BBFF	RO	2x128	N/A	MSA Reserved
BC00	BFFF	RW	1024	16	MSA-100GLH Module VR2: Bulk Data Transfer Registers

2.5 User NVR Restore and Save Function (0xB004)

To write permanently to User NVR registers (0x8000 → 0x9F00) the host shall use the “Save” function to store the shadowed NVR data into underlying NVM. The host only needs to perform a single save operation to copy the entire User NVR shadow registers to the underlying NVM after finishing editing the data.

Upon power-up or reset the User NVR shadow registers are “Restored” with NVM values. Note that the Restore function will overwrite the NVR shadow registers, losing any host-written values in them that have occurred since the last Save to the underlying NVM.

The NVR Access Control Register (**B004h**) provides the Save function for Host to save the User NVRs content.

Bit 5 in NVR Access Control Register is designated for User NVR save command.

A “1” written to bit 5 in register **B004h** initiates a User NVR Save.

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	Init Value
B004	1			NVR Access Control		0000h
		WO	5	User Restore and Save command	1: Save the user NVR section	0

So to call the user NVR save command user can write 0x0020 into register 0xB004.

The Save NVR duration is around 0.5 seconds. When this function is called it should be followed by a 0.5 second time wait.

During this process the user can't write or read CFP registers.

2.6 PRG_ALRM_s

The signals HIPWR_ON, MOD_READY, and MODFAULT are CFP internally generated signals and are defaults of the programmable alarm pins PRG_ALRM_x.

The Following Table lists the corresponding functions for each of the PRG_ALRM_s.

NAME	ALARM SOURCE	VALUE
HIPWR_ON	Module high-power-on indicator. PRG_ALRM1 MSA default.	0: Module not high powered up 1: Module high power up completed
MOD_READY	MOD_READY, module startup sequence done, PRG_ALRM2 MSA default.	0: Not done 1: Done
MOD_FAULT	Fault detected. PRG_ALRM3 MSA default.	0: No Fault 1: Fault

For testing purposes, PRG_ALRM3 can be manually controlled via bit 0 of register 0x9405.

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	Init Value
9405	1			PRG_ALRM control register		0000h
		RW	0	PRG_ALRM3	0: De-assert PRG_ALRM3 pin 1: Assert PRG_ALRM3 pin	0

2.7 RX_LOS

The ML4030-ACO initially implements RX_LOS to follow TX_DIS input, assuming that in a loopback module, when the host transmitters are disabled, no data should be received thus leading to RX_LOS condition.

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	Init Value
9404	1			Custom Alarms		0000h
		RW	0	Prog RX_LOS	0: RX_LOS default operation (RX_LOS= TX_DIS) 1: Programmable RX_LOS (driven as per Soft RX_LOS bit)	0
		RW	1	Soft RX_LOS	0: RX_LOS HW signal set to LOW	0

				1: RX_LOS HW signal set to High	
--	--	--	--	---------------------------------	--

2.8 Temperature Monitor

The alarms and warnings of the CFP2 Loopback are listed in the tables below. Alarms and Warnings are set in register 0xB01F in bits 8,9,10 and 11, and are continuously asserted and de-asserted when the corresponding alarms/warnings occur. addresses 0x8080, 0x8082, 0x8084, and 0x8086 are reference registers for temperature alarms and warnings, they contain the default values (HA:75, HW:65, LW:2 and LA:0) and can be changed when desired. The module is continuously reading the temperature and storing its value in Register 0xB02F.

When the temperature reaches the High Alarm values, the module front LED indicator will begin blinking.

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	LSB Unit
8080	2	RW	7~0	Temp High Alarm Threshold	These thresholds are a signed 16-bit integer with LSB = 1/256 of a degree Celsius representing a range from -128 to + 127 255/256 degree C. MSA valid range is between -40 and +125C." MSB stored at low address, LSB stored at high address.	1/256 degC
8082	2	RW	7~0	Temp High Warning Threshold		
8084	2	RO	7~0	Temp Low Warning Threshold		
8086	2	RO	7~0	Temp Low Alarm Threshold		

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	Init Value
B01F	1	RO		Module Alarms and Warnings 1		0000h
			11	Mod Temp High Alarm	Mod temp high Alarm 0: Normal, 1: Asserted	0
			10	Mod Temp High Warning	Mod temp high Warning 0: Normal, 1: Asserted	0
			9	Mod Temp Low Warning	Mod temp high Warning 0: Normal, 1: Asserted	0
			8	Mod Temp Low Alarm	Mod temp Low Alarm 0: Normal, 1: Asserted	0

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	Init Value
B02F	1	RO		Module Temp Monitor A/D Value	Internally measured temperature in degrees Celsius, a 16-bit signed integer with LSB = 1/256 of a degree Celsius, representing a total range from -128 to + 127 255/256 degC. MSA valid range is between -40 and +125C. Accuracy shall be better than +/- 3 degC over the whole temperature range.	0000h

2.9 Insertion Counter

The Insertion counter contains the number of times the module was plugged in a host. The insertion counter is incremented every time the module enters an initializing sequence, as it is nonvolatile it is always saved, and can be read anytime from register 0x9400.

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	LSBUnit
9400	1			Insertion Counter		
		RO	0~7	Insertion Count	Number of times the modules was plugged in a host	1 insertion

2.10 Programmable Power Dissipation & Thermal Emulation

Register 0x9401 is used for PWM control over MDIO. It is an 8 bit data register.

The consumed power changes accordingly when the value in this register is changed (only when in high power mode). In Low power mode the module automatically turns off PWM.

The values written in this register can be stored by calling the Save NVR function, thus the user can permanently change the initial power consumed in high power mode when the module is powered up by setting the register value and calling the Save NVR function.

The PWM can also be used for module thermal emulation. The module contains a thermal spot positioned where the optical transceivers usually are in an optical module that is heated relative to the related PWM register.

Note that the led starts blinking when the temperature high alarm is reached.

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	Init Value
9401	1			PWM		
		RW	0~7	PWM	0x00 to 0xFF corresponding to 0 to 12W power cons	0

2.11 Cut-Off Temperature

To avoid overheating the module, a Cut-Off Temperature is defined in Register 0x9402.

The module is continuously monitoring the temperature and checking its value against the Cut-Off temperature. A Temperature Cut-Off register is defined at address 0x9402, once the module temperature reaches the cut-off temperature, the PWM will automatically turn off in order to prevent overheating. Once the module gets below cut-off value of the temperature, the PWM goes back to its previous value.

The Maximum allowed Cut-Off temperature for the ML4030-ACO is 85degC, so even if the value stored in register 0x9402 is higher than 85 the module will still Cut-Off power at 85degC, in case the value stored in 0x9402 is lower than 85 then it will be adopted instead of the default value.

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	DefultValue
9402	1			Temp Cut-Off		
		RW	0~7	Cut-Off Value	0x00 to 0x55 (0 to 85degC)	0x55

2.12 Module Control and Status Registers

The below registers are implemented, and can be checked for module State and Control.

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	Init Value
B010	1			Module General Control		0000h
		RO	15	Soft Module Reset	Register bit for module reset function. Writing a 0 to this bit has no effect regardless it was 0 or 1 previously. 1: Module reset assert	0
		RW	14	Soft Module Low Power	Register bit for module low power function. 1: Assert	0
		RW	13	Soft TX_Disable	Register bit for TX Disable function. 1: Assert	0
		RO	12-10	Reserved		0
		RW	9	Soft GLB_ALRM Test	Command bit for software forced test signal. When this bit is asserted it generates GLB_ALRM signal. 1: Assert	0
		RO	8-6	Reserved		0
		RO	5	TX_DIS Pin State	Logical state of the TX_DIS pin. 1: Assert.	0
		RO	4	MOD_LOPWR Pin State	Logical state of the MOD_LOPWR pin. 1: Assert.	0
		RO	3	PRG_CNTL3 Pin State	Logical state of the PRG_CNTL3 pin	0
		RO	2	PRG_CNTL2 Pin State	Logical state of the PRG_CNTL2 pin	0
		RO	1	PRG_CNTL1 Pin State	Logical state of the PRG_CNTL1 pin	0
		RO	0	Reserved		0

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	Init Value
B016	1			Module State		0000h
		RO	15~9	Reserved		0
			8	High-Power-down State	1: Corresponding state is active. Word value = 0100h.	0
			7	TX-Turn-off State	1: Corresponding state is active. Word value = 0080h.	0
			6	Fault State	1: Corresponding state is active. Word value = 0040h.	0
			5	Ready State	1: Corresponding state is active. Word value = 0020h.	0
			4	TX-Turn-on State	1: Corresponding state is active. Word value = 0010h.	0
			3	TX-Off State	1: Corresponding state is active. Word value = 0008h.	0
			2	High-Power-up State	1: Corresponding state is active. Word value = 0004h.	0
			1	Low-Power State	1: Corresponding state is active. Word value = 0002h.	0
			0	Initialize State	1: Corresponding state is active. Word value = 0001h.	0

Hex Adr	Size	Access Type	Bit	Register Name Bit Field Name	Description	Init Value
B01D	1			Module General Status		
		RO	1	HIPWR_ON	Status bit representing the condition of module in high power status. FAWS Type is not applicable. 0: Module is not in high power on status, 1: Module is in high powered on status.	0

3. CFP2-ACO Pin Allocation

CFP2-ACO class 3 pin mapping is adopted for the ML4030-ACO; the same pin mapping is compatible for using it as an Electrical loopback module for classes 1, 2 and 3.

	CFP2-ACO	CFP2-ACO
	Bottom: Class 3	Top: Class 3
1	GND	104 GND
2*	X OUTER PHASE DITHER	103* XI PHASE DITHER
3*	Y OUTER PHASE DITHER	102 N.C.
4	GND	101 GND
5*	TX X POL. TAP	100* TX_Xip (RF Mapping [0,0,0])
6*	TX Y POL. TAP	99* TX_Xin (RF Mapping [0,0,0])
7	3.3V_GND	98 GND
8	3.3V_GND	97* TX_XQp (RF Mapping [0,0,0])
9	3.3V	96* TX_XQn (RF Mapping [0,0,0])
10	3.3V	95 GND
11	3.3V	94 N.C.
12	3.3V	93* XQ PHASE DITHER
13	3.3V_GND	92 GND
14	3.3V_GND	91* YI PHASE DITHER
15	VND_IO_A	90 N.C.
16	VND_IO_B	89 GND
17	PRG_CNTL1	88* TX_Yip (RF Mapping [0,0,0])
18	PRG_CNTL2	87* TX_Yin (RF Mapping [0,0,0])
19	PRG_CNTL3	86 GND
20	PRG_ALRM1	85* TX_YQp (RF Mapping [0,0,0])
21	PRG_ALRM2	84* TX_YQn (RF Mapping [0,0,0])
22	PRG_ALRM3	83 GND
23	GND	82 N.C.
24*	TX_DIS (PRG_CNTL)	81* YQ PHASE DITHER
25*	RX_LOS (PRG_ALRM)	80 GND
26	MOD_LOPWR	79* (REFCLKn-Terminated)
27	MOD_ABS	78* (REFCLKp-Terminated)
28	MOD_RSTn	77 GND
29	GLB_ALRMn	76* TX_X-POL POWER DITHER
30	GND	75* TX_Y-POL POWER DITHER
31	MDC	74 GND
32	MDIO	73* RX_Xip (RF Mapping [0,0,0])
33	PRTADR0	72* RX_Xin (RF Mapping [0,0,0])
34	PRTADR1	71 GND
35	PRTADR2	70* RX_XQp (RF Mapping [0,0,0])
36	VND_IO_C	69* RX_XQn (RF Mapping [0,0,0])
37	VND_IO_D	68 GND
38	VND_IO_E	67* Rx MGC XI
39	3.3V_GND	66* Rx MGC XQ
40	3.3V_GND	65 GND
41	3.3V	64* Rx MGC YI
42	3.3V	63* Rx MGC YQ
43	3.3V	62 GND
44	3.3V	61* RX_Yip (RF Mapping [0,0,0])
45	3.3V_GND	60* RX_Yin (RF Mapping [0,0,0])
46	3.3V_GND	59 GND
47*	TX_XI_TAP	58* RX_YQp (RF Mapping [0,0,0])
48*	TX_XQ_TAP	57* RX_YQn (RF Mapping [0,0,0])
49	GND	56 GND
50*	TX_YI_TAP	55* PM-SYNC
51*	TX_YQ_TAP	54* TX_POST_POL_MUX_TAP
52	GND	53 GND

3.1 High Speed Signals

High speed signals are electrically looped back from the TX side to the RX side of the module, all differential TX pairs are connected to the corresponding RX pairs, and the signals are AC coupled as specified by CFP MSA HW specs.

The Passive traces connecting TX to RX pairs are designed to support a data rate up to 32 Gbps.

4. NVR Register preloaded values

The following table shows the values preloaded by Multilane to the NVR registers as Basic and extended ID registers.

The vendor part number **ML4030-ACO-2** set at registers 8034h to 803Fh identify a Rev B module.

Address	Hex	Decimal	ASCII	MSA Description
CFP NVR 1 32768(8000h)	0x14	20		Module Identifier
CFP NVR 1 32769(8001h)	0x20	32		Extended Identifier
CFP NVR 1 32770(8002h)	0x00	0		Connector Type Code
CFP NVR 1 32771(8003h)	0x00	0		Ethernet Application Code
CFP NVR 1 32772(8004h)	0x00	0		Fiber Channel Application Code
CFP NVR 1 32773(8005h)	0x00	0		Copper Link Application Code
CFP NVR 1 32774(8006h)	0x00	0		SONET/SDH Application Code
CFP NVR 1 32775(8007h)	0x00	0		OTN Application Code
CFP NVR 1 32776(8008h)	0x1F	31		Additional Capable Rates Supported
CFP NVR 1 32777(8009h)	0x44	68	D	Number of Lanes Supported
CFP NVR 1 32778(800Ah)	0xC4	196	?	Media Properties
CFP NVR 1 32779(800Bh)	0x00	0		Maximum Network Lane Bit Rate
CFP NVR 1 32780(800Ch)	0xA0	160	?	Maximum Host Lane Bit Rate
CFP NVR 1 32781(800Dh)	0x00	0		Maximum Single Mode Optical Fiber Length
CFP NVR 1 32782(800Eh)	0x00	0		Maximum Multi-Mode Optical Fiber Length
CFP NVR 1 32783(800Fh)	0x00	0		Maximum Copper Cable Length
CFP NVR 1 32784(8010h)	0x00	0		Transmitter Spectral Characteristics 1
CFP NVR 1 32785(8011h)	0x00	0		Transmitter Spectral Characteristics 2
CFP NVR 1 32786(8012h)	0x00	0		Minimum Wavelength per Active Fiber
CFP NVR 1 32787(8013h)	0x00	0		Minimum Wavelength per Active Fiber
CFP NVR 1 32788(8014h)	0x00	0		Maximum Wavelength per Active Fiber
CFP NVR 1 32789(8015h)	0x00	0		Maximum Wavelength per Active Fiber
CFP NVR 1 32790(8016h)	0x00	0		Maximum per Lane Optical Width
CFP NVR 1 32791(8017h)	0x00	0		Maximum per Lane Optical Width
CFP NVR 1 32792(8018h)	0x44	68	D	Device Technology 1
CFP NVR 1 32793(8019h)	0x00	0		Device Technology 2
CFP NVR 1 32794(801Ah)	0x00	0		Signal Code

CFP NVR 1 32795(801Bh)	0x00	0		Maximum Total Optical Output Power per Connector
CFP NVR 1 32796(801Ch)	0x00	0		Maximum Optical Input Power per Network Lane
CFP NVR 1 32797(801Dh)	0x46	70	F	Maximum Power Consumption
CFP NVR 1 32798(801Eh)	0x05	5		Maximum Power Consumption in Low Power Mode
CFP NVR 1 32799(801Fh)	0x55	85	U	Maximum Operating Case Temp Range
CFP NVR 1 32800(8020h)	0x00	0		Minimum Operating Case Temp Range
CFP NVR 1 32801(8021h)	0x4D	77	M	Vendor Name
CFP NVR 1 32802(8022h)	0x55	85	U	Vendor Name
CFP NVR 1 32803(8023h)	0x4C	76	L	Vendor Name
CFP NVR 1 32804(8024h)	0x54	84	T	Vendor Name
CFP NVR 1 32805(8025h)	0x49	73	I	Vendor Name
CFP NVR 1 32806(8026h)	0x4C	76	L	Vendor Name
CFP NVR 1 32807(8027h)	0x41	65	A	Vendor Name
CFP NVR 1 32808(8028h)	0x4E	78	N	Vendor Name
CFP NVR 1 32809(8029h)	0x45	69	E	Vendor Name
CFP NVR 1 32810(802Ah)	0x20	32		Vendor Name
CFP NVR 1 32811(802Bh)	0x53	83	S	Vendor Name
CFP NVR 1 32812(802Ch)	0x41	65	A	Vendor Name
CFP NVR 1 32813(802Dh)	0x4C	76	L	Vendor Name
CFP NVR 1 32814(802Eh)	0x20	32		Vendor Name
CFP NVR 1 32815(802Fh)	0x20	32		Vendor Name
CFP NVR 1 32816(8030h)	0x20	32		Vendor Name
CFP NVR 1 32817(8031h)	0x00	0		Vendor OUI
CFP NVR 1 32818(8032h)	0x00	0		Vendor OUI
CFP NVR 1 32819(8033h)	0x00	0		Vendor OUI
CFP NVR 1 32820(8034h)	0x4D	77	M	Vendor Part Number
CFP NVR 1 32821(8035h)	0x4C	76	L	Vendor Part Number
CFP NVR 1 32822(8036h)	0x34	52	4	Vendor Part Number
CFP NVR 1 32823(8037h)	0x30	48	0	Vendor Part Number
CFP NVR 1 32824(8038h)	0x33	51	3	Vendor Part Number
CFP NVR 1 32825(8039h)	0x30	48	0	Vendor Part Number
CFP NVR 1 32826(803Ah)	0x2D	45	-	Vendor Part Number
CFP NVR 1 32827(803Bh)	0x41	65	A	Vendor Part Number
CFP NVR 1 32828(803Ch)	0x43	67	C	Vendor Part Number
CFP NVR 1 32829(803Dh)	0x4F	79	O	Vendor Part Number
CFP NVR 1 32830(803Eh)	0x2D	45	-	Vendor Part Number
CFP NVR 1 32831(803Fh)	0x32	50	2	Vendor Part Number
CFP NVR 1 32832(8040h)	0x20	32		Vendor Part Number
CFP NVR 1 32833(8041h)	0x20	32		Vendor Part Number
CFP NVR 1 32834(8042h)	0x20	32		Vendor Part Number
CFP NVR 1 32835(8043h)	0x20	32		Vendor Part Number

CFP NVR 1 32836(8044h)	0x20	32	Vendor Serial Number
CFP NVR 1 32837(8045h)	0x20	32	Vendor Serial Number
CFP NVR 1 32838(8046h)	0x20	32	Vendor Serial Number
CFP NVR 1 32839(8047h)	0x20	32	Vendor Serial Number
CFP NVR 1 32840(8048h)	0x20	32	Vendor Serial Number
CFP NVR 1 32841(8049h)	0x20	32	Vendor Serial Number
CFP NVR 1 32842(804Ah)	0x20	32	Vendor Serial Number
CFP NVR 1 32843(804Bh)	0x20	32	Vendor Serial Number
CFP NVR 1 32844(804Ch)	0x20	32	Vendor Serial Number
CFP NVR 1 32845(804Dh)	0x20	32	Vendor Serial Number
CFP NVR 1 32846(804Eh)	0x20	32	Vendor Serial Number
CFP NVR 1 32847(804Fh)	0x20	32	Vendor Serial Number
CFP NVR 1 32848(8050h)	0x20	32	Vendor Serial Number
CFP NVR 1 32849(8051h)	0x20	32	Vendor Serial Number
CFP NVR 1 32850(8052h)	0x20	32	Vendor Serial Number
CFP NVR 1 32851(8053h)	0x20	32	Vendor Serial Number
CFP NVR 1 32852(8054h)	0x32	50	2 Date Code
CFP NVR 1 32853(8055h)	0x30	48	0 Date Code
CFP NVR 1 32854(8056h)	0x31	49	1 Date Code
CFP NVR 1 32855(8057h)	0x35	53	5 Date Code
CFP NVR 1 32856(8058h)	0x30	48	0 Date Code
CFP NVR 1 32857(8059h)	0x36	54	6 Date Code
CFP NVR 1 32858(805Ah)	0x30	48	0 Date Code
CFP NVR 1 32859(805Bh)	0x02	2	Date Code
CFP NVR 1 32860(805Ch)	0x00	0	Lot Code
CFP NVR 1 32861(805Dh)	0x00	0	Lot Code
CFP NVR 1 32862(805Eh)	0x00	0	CLEI Code
CFP NVR 1 32863(805Fh)	0x00	0	CLEI Code
CFP NVR 1 32864(8060h)	0x00	0	CLEI Code
CFP NVR 1 32865(8061h)	0x00	0	CLEI Code
CFP NVR 1 32866(8062h)	0x00	0	CLEI Code
CFP NVR 1 32867(8063h)	0x00	0	CLEI Code
CFP NVR 1 32868(8064h)	0x00	0	CLEI Code
CFP NVR 1 32869(8065h)	0x00	0	CLEI Code
CFP NVR 1 32870(8066h)	0x00	0	CLEI Code
CFP NVR 1 32871(8067h)	0x00	0	CLEI Code
CFP NVR 1 32872(8068h)	0x0E	14	CFP MSA Hardware Specification Revision Number
CFP NVR 1 32873(8069h)	0x16	22	CFP MSA Management Interface Specification Revision
CFP NVR 1 32874(806Ah)	0x02	2	Module Hardware Version Number
CFP NVR 1 32875(806Bh)	0x00	0	Module Hardware Version Number

CFP NVR 1 32876(806Ch)	0x01	1		Module Firmware Version Number
CFP NVR 1 32877(806Dh)	0x00	0		Module Firmware Version Number
CFP NVR 1 32878(806Eh)	0x00	0		Digital Diagnostic Monitoring Type
CFP NVR 1 32879(806Fh)	0x01	1		Digital Diagnostic Monitoring Capability 1
CFP NVR 1 32880(8070h)	0x00	0		Digital Diagnostic Monitoring Capability 2
CFP NVR 1 32881(8071h)	0x80	128	?	Module Enhanced Options
CFP NVR 1 32882(8072h)	0x01	1		Maximum High-Power-up Time
CFP NVR 1 32883(8073h)	0x01	1		Maximum TX-Turn-on Time
CFP NVR 1 32884(8074h)	0x00	0		Host Lane Signal Spec
CFP NVR 1 32885(8075h)	0x00	0		Heat Sink Type
CFP NVR 1 32886(8076h)	0x01	1		Maximum TX-Turn-off Time
CFP NVR 1 32887(8077h)	0x01	1		Maximum High-Power-down Time
CFP NVR 1 32888(8078h)	0x00	0		Module Enhanced Options 2
CFP NVR 1 32889(8079h)	0xA3	163	?	Transmitter Monitor Clock Options
CFP NVR 1 32890(807Ah)	0xA3	163	?	Receiver Monitor Clock Options
CFP NVR 1 32891(807Bh)	0x00	0		Reserved
CFP NVR 1 32892(807Ch)	0x00	0		Reserved
CFP NVR 1 32893(807Dh)	0x00	0		Reserved
CFP NVR 1 32894(807Eh)	0x00	0		Reserved
CFP NVR 1 32895(807Fh)	0x00	0		CFP NVR 1 Checksum
CFP NVR 2 32896(8080h)	0x4B	75	K	Transceiver Temp High Alarm Threshold
CFP NVR 2 32897(8081h)	0x00	0		Transceiver Temp High Alarm Threshold
CFP NVR 2 32898(8082h)	0x41	65	A	Transceiver Temp High Warning Threshold
CFP NVR 2 32899(8083h)	0x00	0		Transceiver Temp High Warning Threshold
CFP NVR 2 32900(8084h)	0x05	5		Transceiver Temp Low Warning Threshold
CFP NVR 2 32901(8085h)	0x00	0		Transceiver Temp Low Warning Threshold
CFP NVR 2 32902(8086h)	0x00	0		Transceiver Temp Low Alarm Threshold
CFP NVR 2 32903(8087h)	0x00	0		Transceiver Temp Low Alarm Threshold
CFP NVR 2 32904(8088h)	0x00	0		VCC High Alarm Threshold
CFP NVR 2 32905(8089h)	0x00	0		VCC High Alarm Threshold
CFP NVR 2 32906(808Ah)	0x00	0		VCC High Warning Threshold
CFP NVR 2 32907(808Bh)	0x00	0		VCC High Warning Threshold
CFP NVR 2 32908(808Ch)	0x00	0		VCC Low Warning Threshold
CFP NVR 2 32909(808Dh)	0x00	0		VCC Low Warning Threshold
CFP NVR 2 32910(808Eh)	0x00	0		VCC Low Alarm Threshold
CFP NVR 2 32911(808Fh)	0x00	0		VCC Low Alarm Threshold

CFP NVR 2 32912(8090h)	0x00	0	SOA Bias Current High Alarm Threshold
CFP NVR 2 32913(8091h)	0x00	0	SOA Bias Current High Alarm Threshold
CFP NVR 2 32914(8092h)	0x00	0	SOA Bias Current High Warning Threshold
CFP NVR 2 32915(8093h)	0x00	0	SOA Bias Current High Warning Threshold
CFP NVR 2 32916(8094h)	0x00	0	SOA Bias Current Low Warning Threshold
CFP NVR 2 32917(8095h)	0x00	0	SOA Bias Current Low Warning Threshold
CFP NVR 2 32918(8096h)	0x00	0	SOA Bias Current Low Alarm Threshold
CFP NVR 2 32919(8097h)	0x00	0	SOA Bias Current Low Alarm Threshold
CFP NVR 2 32920(8098h)	0x00	0	Auxiliary 1 Monitor High Alarm Threshold
CFP NVR 2 32921(8099h)	0x00	0	Auxiliary 1 Monitor High Alarm Threshold
CFP NVR 2 32922(809Ah)	0x00	0	Auxiliary 1 Monitor High Warning Threshold
CFP NVR 2 32923(809Bh)	0x00	0	Auxiliary 1 Monitor High Warning Threshold
CFP NVR 2 32924(809Ch)	0x00	0	Auxiliary 1 Monitor Low Warning Threshold
CFP NVR 2 32925(809Dh)	0x00	0	Auxiliary 1 Monitor Low Warning Threshold
CFP NVR 2 32926(809Eh)	0x00	0	Auxiliary 1 Monitor Low Alarm Threshold
CFP NVR 2 32927(809Fh)	0x00	0	Auxiliary 1 Monitor Low Alarm Threshold
CFP NVR 2 32928(80A0h)	0x00	0	Auxiliary 2 Monitor High Alarm Threshold
CFP NVR 2 32929(80A1h)	0x00	0	Auxiliary 2 Monitor High Alarm Threshold
CFP NVR 2 32930(80A2h)	0x00	0	Auxiliary 2 Monitor High Warning Threshold
CFP NVR 2 32931(80A3h)	0x00	0	Auxiliary 2 Monitor High Warning Threshold
CFP NVR 2 32932(80A4h)	0x00	0	Auxiliary 2 Monitor Low Warning Threshold
CFP NVR 2 32933(80A5h)	0x00	0	Auxiliary 2 Monitor Low Warning Threshold
CFP NVR 2 32934(80A6h)	0x00	0	Auxiliary 2 Monitor Low Alarm Threshold
CFP NVR 2 32935(80A7h)	0x00	0	Auxiliary 2 Monitor Low Alarm Threshold
CFP NVR 2 32936(80A8h)	0x00	0	Laser Bias Current High Alarm Threshold
CFP NVR 2 32937(80A9h)	0x00	0	Laser Bias Current High Alarm Threshold
CFP NVR 2 32938(80AAh)	0x00	0	Laser Bias Current High Warning Threshold
CFP NVR 2 32939(80ABh)	0x00	0	Laser Bias Current High Warning Threshold
CFP NVR 2 32940(80ACh)	0x00	0	Laser Bias Current Low WarningThreshold
CFP NVR 2 32941(80ADh)	0x00	0	Laser Bias Current Low WarningThreshold
CFP NVR 2 32942(80AEh)	0x00	0	Laser Bias Current Low Alarm Threshold
CFP NVR 2 32943(80AFh)	0x00	0	Laser Bias Current Low Alarm Threshold
CFP NVR 2 32944(80B0h)	0x00	0	Laser Output Power High Alarm Threshold
CFP NVR 2 32945(80B1h)	0x00	0	Laser Output Power High Alarm Threshold
CFP NVR 2 32946(80B2h)	0x00	0	Laser Output Power High Warning Threshold
CFP NVR 2 32947(80B3h)	0x00	0	Laser Output Power High Warning Threshold
CFP NVR 2 32948(80B4h)	0x00	0	Laser Output Power Low Warning Threshold
CFP NVR 2 32949(80B5h)	0x00	0	Laser Output Power Low Warning Threshold
CFP NVR 2 32950(80B6h)	0x00	0	Laser Output Power Low Alarm Threshold
CFP NVR 2 32951(80B7h)	0x00	0	Laser Output Power Low Alarm Threshold
CFP NVR 2 32952(80B8h)	0x00	0	Laser Temperature High Alarm Threshold
CFP NVR 2 32953(80B9h)	0x00	0	Laser Temperature High Alarm Threshold

CFP NVR 2 32954(80BAh)	0x00	0	Laser Temperature High WarningThreshold
CFP NVR 2 32955(80BBh)	0x00	0	Laser Temperature High Warning Threshold
CFP NVR 2 32956(80BCh)	0x00	0	Laser Temperature Low Warning Threshold
CFP NVR 2 32957(80BDh)	0x00	0	Laser Temperature Low Warning Threshold
CFP NVR 2 32958(80BEh)	0x00	0	Laser Temperature Low Alarm Threshold
CFP NVR 2 32959(80BFh)	0x00	0	Laser Temperature Low Alarm Threshold
CFP NVR 2 32960(80C0h)	0x00	0	Receive Optical Power High Alarm Threshold
CFP NVR 2 32961(80C1h)	0x00	0	Receive Optical Power High Alarm Threshold
CFP NVR 2 32962(80C2h)	0x00	0	Receive Optical Power High Warning Threshold
CFP NVR 2 32963(80C3h)	0x00	0	Receive Optical Power High Warning Threshold
CFP NVR 2 32964(80C4h)	0x00	0	Receive Optical Power Low Warning Threshold
CFP NVR 2 32965(80C5h)	0x00	0	Receive Optical Power Low Warning Threshold
CFP NVR 2 32966(80C6h)	0x00	0	Receive Optical Power Low Alarm Threshold
CFP NVR 2 32967(80C7h)	0x00	0	Receive Optical Power Low Alarm Threshold
CFP NVR 2 32968(80C8h)	0x00	0	Reserved
CFP NVR 2 32969(80C9h)	0x00	0	Reserved
CFP NVR 2 32970(80CAh)	0x00	0	Reserved
CFP NVR 2 32971(80CBh)	0x00	0	Reserved
CFP NVR 2 32972(80CCh)	0x00	0	Reserved
CFP NVR 2 32973(80CDh)	0x00	0	Reserved
CFP NVR 2 32974(80CEh)	0x00	0	Reserved
CFP NVR 2 32975(80CFh)	0x00	0	Reserved
CFP NVR 2 32976(80D0h)	0x00	0	Reserved
CFP NVR 2 32977(80D1h)	0x00	0	Reserved
CFP NVR 2 32978(80D2h)	0x00	0	Reserved
CFP NVR 2 32979(80D3h)	0x00	0	Reserved
CFP NVR 2 32980(80D4h)	0x00	0	Reserved
CFP NVR 2 32981(80D5h)	0x00	0	Reserved
CFP NVR 2 32982(80D6h)	0x00	0	Reserved
CFP NVR 2 32983(80D7h)	0x00	0	Reserved
CFP NVR 2 32984(80D8h)	0x00	0	Reserved
CFP NVR 2 32985(80D9h)	0x00	0	Reserved
CFP NVR 2 32986(80DAh)	0x00	0	Reserved
CFP NVR 2 32987(80DBh)	0x00	0	Reserved
CFP NVR 2 32988(80DCh)	0x00	0	Reserved
CFP NVR 2 32989(80DDh)	0x00	0	Reserved
CFP NVR 2 32990(80DEh)	0x00	0	Reserved
CFP NVR 2 32991(80DFh)	0x00	0	Reserved
CFP NVR 2 32992(80E0h)	0x00	0	Reserved
CFP NVR 2 32993(80E1h)	0x00	0	Reserved
CFP NVR 2 32994(80E2h)	0x00	0	Reserved
CFP NVR 2 32995(80E3h)	0x00	0	Reserved

CFP NVR 2 32996(80E4h)	0x00	0	Reserved
CFP NVR 2 32997(80E5h)	0x00	0	Reserved
CFP NVR 2 32998(80E6h)	0x00	0	Reserved
CFP NVR 2 32999(80E7h)	0x00	0	Reserved
CFP NVR 2 33000(80E8h)	0x00	0	Reserved
CFP NVR 2 33001(80E9h)	0x00	0	Reserved
CFP NVR 2 33002(80EAh)	0x00	0	Reserved
CFP NVR 2 33003(80EBh)	0x00	0	Reserved
CFP NVR 2 33004(80ECh)	0x00	0	Reserved
CFP NVR 2 33005(80EDh)	0x00	0	Reserved
CFP NVR 2 33006(80EEh)	0x00	0	Reserved
CFP NVR 2 33007(80EFh)	0x00	0	Reserved
CFP NVR 2 33008(80F0h)	0x00	0	Reserved
CFP NVR 2 33009(80F1h)	0x00	0	Reserved
CFP NVR 2 33010(80F2h)	0x00	0	Reserved
CFP NVR 2 33011(80F3h)	0x00	0	Reserved
CFP NVR 2 33012(80F4h)	0x00	0	Reserved
CFP NVR 2 33013(80F5h)	0x00	0	Reserved
CFP NVR 2 33014(80F6h)	0x00	0	Reserved
CFP NVR 2 33015(80F7h)	0x00	0	Reserved
CFP NVR 2 33016(80F8h)	0x00	0	Reserved
CFP NVR 2 33017(80F9h)	0x00	0	Reserved
CFP NVR 2 33018(80FAh)	0x00	0	Reserved
CFP NVR 2 33019(80FBh)	0x00	0	Reserved
CFP NVR 2 33020(80FCh)	0x00	0	Reserved
CFP NVR 2 33021(80FDh)	0x00	0	Reserved
CFP NVR 2 33022(80FEh)	0x00	0	Reserved
CFP NVR 2 33023(80FFh)	0x8E	142	?
			CFP NVR 2 Checksum

Revision History

Revision number	Date	Description
0.1	28/08/2015	Preliminary

Author Mary DAOU

North America
48521 Warm Springs Blvd. Suite 310
Fremont, CA 94539
USA
+1 510 573 6388

Worldwide
Houmal Technology Park
Askarieh Main Road
Houmal, Lebanon
+961 5 941 668

Asia
14F-5/ Rm.5, 14F., No 295
Sec.2, Guangfu Rd. East Dist.,
Hsinchu City 300, Taiwan (R.O.C)
+886 3 5744 591